



**100V Volume Control
AP-VC5 / AP-VC30 / AP-VC60 / AP-VC120**



**AP-VC5 / AP-VC30 / AP-VC60 / AP-VC120
100V Volume Control**

Features :

- PA (Public address) system use 100V volume control.
- Background music system use 100 volt attenuator.
- Classic range volume controller for cost-effective system use.
- The volume controller is used to adjust the loudspeaker output in the room.
- The volume controller is used to keep same output level for one same speaker line, because the end the speaker line signal loss is rather big, so its outputs is less, thus volume controller is added to the front of the line to lower the speaker output so as to keep the similar ambient output level for the all of the speaker in the same line.
- High level white UV-protected ABS material to integrate together with the white wall and architecture design.
- Built-in transformer to control the PA 100V or 70V line loudspeakers.
- With 4 levels of volume attenuator and one position of off.
- Surface wall mount or in-wall mounting box shall be purchased separated.

Commercial Building



School Campus



Transportation



Technical Specifications

Model No	AP-VC5	AP-VC30	AP-VC60	AP-VC120	
Description	100V Volume Control				
Rated Power Output	6W	30W	60W	120W	
Line Input	100V or 70V				
Volume Step	5 steps				
Attenuation Per Step	3dB				
Total Attenuation	33dB				
Material	UV-protected ABS				
Finish	White				
Mounting Way	Surface mount or in-wall mount				
Depth	50MM	60MM	60MM	60MM	
Plate Dimension	86(W)mmx86(D)mm				

Side View, Dimension & Wiring Diagram :

